
Baseus




Baseus Magnetic wireless quick charging power bank 10000mAh 20W

User Manual

Please Read This User Manual Completely And Keep It Properly

Name: Wireless Quick Charging Power Bank

Model No.: PPCXW10
Battery: Polymer battery
Material: ABS+PC
Capacity: 10000mAh/3.7V (37Wh)
Rated capacity: 5800mAh (5V⎓3A)
Energy conversion rate: ≥75%
Type-C input: 5V⎓3A, 9V⎓2A
Wireless charging Output: 15W
USB output: 5V⎓3A, 9V⎓2A, 12V⎓1.5A
Type-C output: 5V⎓3A, 9V⎓2.22A, 12V⎓1.5A
USB+Type-C: 5V⎓3A
Total Output: 5V⎓3A



Packing list:



Power Bank*1 User Manual*1 Warranty card*1 Charging Cable*1

Product description:

This product is a portable charging device that can provide wired or wireless charging for mobile phones, tablets, e-books, game machines and other digital products. The product has the characteristics of two in one of wired charging and wireless charging, magnetic suction positioning, power digital display, p20w pd fast charging, three output (including wireless output), 15W wireless fast charging, etc. Product built-in FOD, overcharge, over discharge, temperature protection and other safety protection circuit.

Operation description

The power button operation instructions:

For viewing electric quantity:

Press the button once to initiate the power output function, when you can view the remaining electric level of the power bank. After lit for 30sec, the LED indicator will extinguish automatically.

For charging the power bank:

When the charging line matched with the mobile power interface is connected to charge the power supply, the power indicator lights up to show the current power, which means that the connection is normal and the power supply is charged. If the power indicator does not light up after connecting the charging line, it means that the connection fails and there is no charging, please check whether the charging line is connected normally.

Operation for discharging by cable:

Connect the USB charging cable to the corresponding output port of the power supply, and the power supply will automatically turn on the output. Due to compatibility problems, some smart phones need to press the key to turn on the power output function, which is a normal phenomenon and need not be ignored. Press the key once to supply power to the external equipment. Press the key once to output power for about 30 seconds. If there is no external load in 30 seconds, the power output will be automatically turned off.

Operation for discharging by wireless:

When the power indicator lights up for about 30 seconds, the mobile phone will be charged for wireless charging within 30 seconds. If the mobile phone is placed in the wireless charging area of the power supply, the mobile phone can be charged for wireless charging. If there is no wireless charging access within 30 seconds after one key, the product will automatically turn off the wireless charging function.

Wireless charging tips:

The wireless charging mobile phone should be placed in the wireless charging area of the product (the transmitting area of the wireless charging coil is illustrated in the figure) for wireless charging. The wireless charging distance is within 8 mm. If the distance exceeds 8 mm, the wireless charging can not be carried out. Please adjust the wireless charging distance within the wireless charging range.



How to charge this product:

Charging this power bank by using power Adapter/PC USB port.
1、When the original USB cable is chosen for charging this power bank, you may also use Type-c charging cable. The power bank is charged just by inserting it into the Type-c port;
2、Connect the USB connector with the Adapter or PC USB port, then LED electric level indicator begins to flash, indicating this product is being charged. The LED indicator becomes constantly lit when it is fully charged；

Use this product to charge a mobile phone or other digital devices:

1. Check your digital product for its charging voltage, and make sure it matches the output voltage of this product.
2. Use the original charging cable of your digital product. Connect one end of the cable with your digital product and the other end with the output port of this product. The wired output port of this product will be automatically initiated to charge your mobile phone or any other digital product, when the LED indicator becomes constantly lit.
3. To charge a mobile hone with wireless charging function, press the On/Of button once, and the LED indicator is lit. At this point, the power bank is supportive of wireless charging. Place your mobile phone with wireless charging function at the center on the side of the power pack bearing wireless charging mark to begin charging your mobile phone, during which the LED indicator is constantly lit.

Tips:

Please read all instructions and warnings before using this product. Non-standard use will damage the product or personal safety.
1. The charging contact surface on the back of the mobile phone should not be covered with metal materials, such as iron sheet, ring, metal protective case, etc.
2. When the mobile phone is charging, if intermittent charging or serious heating is found, it may be that the receiving coil of the mobile phone is not completely aligned with the wireless charging coil, or there is metal foreign matter in the protective sleeve of the mobile phone. Please try to cool the mobile phone, remove the protective sleeve, and then align it in the correct position.
3. This product has over-current protection function. If the product is used improperly, it will turn off or reduce the output power, reduce the charging speed and ensure safety. Please check whether the equipment is used improperly.
4. Please do not put the product in water, fire medium high temperature environment (more than 45 degrees) and low temperature environment (less than - 20 degrees), do not let children play, especially do not let children contact accessories.
5. Please use a dry soft cloth to clean the surface. Do not use chemicals, soap or detergent.
6. Please do not disassemble the machine by yourself. Improper use or improper placement of the product by the user may reduce the service life or damage the product. Therefore, the responsibility does not belong to the warranty responsibility or the manufacturer's responsibility. Please understand.
7. Mobile power has conversion efficiency, so the battery capacity of mobile power is not equal to the rechargeable capacity.
8. Please charge your power regularly (at least every 5 months is recommended) to maintain its long service life.
9. Improper use of the product may easily result in the product itself or endanger the safety of personal and property.
10. In case of any personal and property damage caused by consumers' improper use or warning in violation of the product instructions, the company will bear all consequences, and the company will not bear any legal liability.
11. Non professionals are strictly prohibited to decompose this product.
12. Avoid using electrical appliances or loads that exceed the output current of the product (the circuit will be protected, no output).
13. Avoid strong physical effects, including knocking, throwing, trampling, squeezing, etc.

Icon description

The 5-year icon refers to the "effective life of environmental protection", not the product quality assurance period. Electronic products all contain toxic and harmful substances such as lead, mercury and cadmium. Once they are overused, toxic and harmful substances may leak or mutate, cause pollution to the environment, or cause serious damage to people and property. The term of "environmental protection use" means that all electronic products will be required to use within this effective period. We will no longer be responsible for the quality of the products due to the safety risks that arise after the safe use period.

Part Description	Toxic or hazardous substances and elements					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent chromium (Cr VI)	Polybrominated biphenyls (PBB)	Polybrominated diphenyl ethers (PBDE)
PCB	X	○	○	○	○	○
Electrode	○	○	○	○	○	○
Battery	X	○	○	○	○	○
Casing	○	○	○	○	○	○

Statement on Toxic and Hazardous Substances in Electronic Information Products

This form is compiled in accordance with SJ/T 11364.
O: It indicates that the content of the toxic and harmful substance in all homogeneous materials of the component is below the limit specified in GB/T 26572 standard.
X: The content of toxic and harmful substances in at least one homogeneous material of this part exceeds the limit stipulated in GB/T 26572 standard.
The product complies with EU ROHS 2.0 directive (2011 / 65 / EU)

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any changes or modifications not expressly approved by the party responsible for compliance
could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

Shenzhen Times Innovation Technology Co., Ltd.
Add: 5th Floor, Building B, Baseus Intelligence Park, No.2008, Xuegang Rd, Gangtou Community, Bantian Street, Longgang District, Shenzhen
Executive Standard: GB/35590-2017
Hotline: +86-4000-712-711 Website: www.baseus.com

PB29562
Designed by Baseus
Made in China